

US010356332B2

(12) United States Patent

Cohen et al.

(54) DUAL APERTURE ZOOM CAMERA WITH VIDEO SUPPORT AND SWITCHING / NON-SWITCHING DYNAMIC CONTROL

- (71) Applicant: Corephotonics Ltd., Tel-Aviv (IL)
- Inventors: Noy Cohen, Tel-Aviv (IL); Oded Gigushinski, Herzlia (IL); Nadav Geva, Tel-Aviv (IL); Gal Shabtay, Tel-Aviv (IL); Ester Ashkenazi, Modi'in (IL); Ruthy Katz, Tel Aviv (IL); Ephraim Goldenberg, Ashdod (IL)
- (73) Assignee: Corephotonics Ltd., Tel Aviv (IL)
- (*) Notice: Subject to any disclaimer, the term of this patent is extended or adjusted under 35 U.S.C. 154(b) by 0 days.
- (21) Appl. No.: 16/241,505
- (22) Filed: Jan. 7, 2019

(65) **Prior Publication Data**

US 2019/0158753 A1 May 23, 2019

Related U.S. Application Data

(63) Continuation of application No. 15/324,720, filed as application No. PCT/IB2016/053803 on Jun. 26, 2016.

(Continued)

(51) **Int. Cl.**

H04N 5/225	(2006.01)
H04N 5/232	(2006.01)

(52) U.S. Cl. CPC H04N 5/23296 (2013.01); H04N 5/2258 (2013.01); H04N 5/23216 (2013.01); H04N 5/23245 (2013.01)

(10) Patent No.: US 10,356,332 B2

(45) **Date of Patent:** Jul. 16, 2019

(58) Field of Classification Search CPC H04N 5/23296; H04N 5/2258; H04N 5/23216; H04N 5/23245 See application file for complete search history.

(56) References Cited

U.S. PATENT DOCUMENTS

4,199,785 A	4/1980 McCullough et al
5,005,083 A	4/1991 Grage et al.
	(Continued)

FOREIGN PATENT DOCUMENTS

CN	101276415 A	10/2008
CN	102739949 A	10/2012
	(Cont	inued)

OTHER PUBLICATIONS

Statistical Modeling and Performance Characterization of a Real-Time Dual Camera Surveillance System, Greienhagen et al., Publisher: IEEE, 2000, 8 pages.

(Continued)

Primary Examiner — Nhan T Tran

(74) Attorney, Agent, or Firm — Natha & Associates; Menachem Nathan

(57) **ABSTRACT**

A dual-aperture zoom digital camera operable in both still and video modes. The camera includes Wide and Tele imaging sections with respective lens/sensor combinations and image signal processors and a camera controller operatively coupled to the Wide and Tele imaging sections. The Wide and Tele imaging sections provide respective image data. The controller is configured to output, in a zoom-in operation between a lower zoom factor (ZF) value and a higher ZF value, a zoom video output image that includes only Wide image data or only Tele image data, depending on whether a no-switching criterion is fulfilled or not.

22 Claims, 5 Drawing Sheets



Related U.S. Application Data

(60) Provisional application No. 62/204,667, filed on Aug. 13, 2015.

(56) **References** Cited

U.S. PATENT DOCUMENTS

5,032,917 A	7/1991	Aschwanden
5,051,830 A	9/1991	von Hoessle
5,248,971 A	9/1993	Mandl
5,287,093 A	2/1994	Amano et al.
5,394,520 A	2/1995	Hall
5,436,660 A	7/1995	Sakamoto
5,444,478 A	8/1995	Lelong et al.
5,459,520 A	10/1995	Sasaki
5,657,402 A	8/1997	Bender et al.
5,682,198 A	10/1997	Katayama et al.
5,768,443 A	6/1998	Michael et al.
5,926,190 A	//1999	Turkowski et al.
5,940,641 A	8/1999	McIntyre et al.
5,982,951 A	11/1999	Katayama et al.
6,101,334 A	8/2000	Fantone
6,128,416 A	10/2000	Oura
6,148,120 A	2/2001	Sussman
0,208,705 BI	3/2001	Bergen
0,208,011 BI	1/2001	Pettersson et al.
0,549,215 BZ	4/2003	Jouppi
0,011,289 BI	8/2003	Yu et al.
0,043,410 BI	11/2003	Daniels et al.
0,000,008 BI	1/2003	Doron
0,080,748 BI	2/2004	Monu Hanna at al
6,714,005 BI	3/2004	rianna et al.
0,724,421 BI	4/2004 5/2004	Giau Davis et el
0,738,073 BZ	5/2004	Park et al.
6,741,230 DI	5/2004	ruman et al.
6,730,903 DI	8/2004	Ivilyatake et al.
0,778,207 BI	8/2004	Lee et al.
7,002,365 BZ	2/2006	Kabb, III Easta at al
7,013,934 DI	5/2006	Floir et al.
7,038,710 D2	3/2000	Oleon et al
7,199,340 D2	4/2007	Labaziewicz et al
7,200,150 B2 7.248.204 B2	7/2007	Slatter
7 256 944 B2	8/2007	Labaziewicz et al
7 305 180 B2	12/2007	Labaziewicz et al.
7.339.621 B2	3/2008	Fortier
7.346.217 B1	3/2008	Gold. Jr.
7.365.793 B2	4/2008	Cheatle et al.
7.411.610 B2	8/2008	Dovle
7.424.218 B2	9/2008	Baudisch et al.
7.509.041 B2	3/2009	Hosono
7,533,819 B2	5/2009	Barkan et al.
7.619.683 B2	11/2009	Davis
7,738,016 B2	6/2010	Toyofuku
7,773,121 B1	8/2010	Huntsberger et al.
7,880,776 B2	2/2011	LeGall et al.
7,918,398 B2	4/2011	Li et al.
7,964,835 B2	6/2011	Olsen et al.
7,978,239 B2	7/2011	Deever et al.
8,115,825 B2	2/2012	Culbert et al.
8,149,327 B2	4/2012	Lin et al.
8,154,610 B2	4/2012	Jo et al.
8,238,695 B1	8/2012	Davey et al.
8,274,552 B2	9/2012	Dahi et al.
8,390,729 B2	3/2013	Long et al.
8,391,697 B2	3/2013	Cho et al.
8,400,555 B1	3/2013	Georgiev et al.
8,439,265 B2	5/2013	Ferren et al.
8,446,484 B2	5/2013	Muukki et al.
8,483,452 B2	7/2013	Ueda et al.
8,514,491 B2	8/2013	Duparre
8,547,389 B2	10/2013	Hoppe et al.
8,553,106 B2	10/2013	Scarff
8,587,691 B2	11/2013	Takane
8,619,148 B1	12/2013	watts et al.
8,803,990 B2	8/2014	Smith
8,896,655 B2	11/2014	Mauchly et al.

8 976 255	B2	3/2015	Matsuoto et al
0.010.297	D2	4/2015	Nalana
9,019,387		4/2013	NaKalio
9,025,073	B2	5/2015	Attar et al.
9,025,077	B2	5/2015	Attar et al.
0.041.835	B 2	5/2015	Honda
0 127 447	D2	0/2015	Ch ihan a
9,137,447	DZ	9/2015	Shibuno
9,185,291	B1 *	11/2015	Shabtay H04N 5/2258
9.215.377	B2	12/2015	Sokeila et al.
0 215 385	B2	12/2015	Luo
0.270.975	D2 D2	2/2015	Dulas davas et al
9,270,875	B 2	2/2016	Brisedoux et al.
9,286,680	B1	3/2016	Jiang et al.
9.344.626	B2	5/2016	Silverstein et al.
0 360 671	B1	6/2016	Zhou
9,300,071	DI	6/2010	
9,309,021	B2	0/2010	Maione et al.
9,413,930	B2	8/2016	Geerds
9.413.984	B2	8/2016	Attar et al.
9 420 180	B2	8/2016	Tin
0 428 702	D2 D2	0/2016	Malvada at al
9,430,792	D2	9/2010	Nakada et al.
9,485,432	BI	11/2016	Medasani et al.
9,578,257	B2	2/2017	Attar et al.
9 618 748	B2	4/2017	Munger et al
0.681.057	D2	6/2017	Attar at al
9,001,037	D2 D2	0/2017	
9,723,220	B2	8/2017	Sugle
9,736,365	B2	8/2017	Laroia
9.736.391	B2	8/2017	Du et al.
9 768 310	B2	9/2017	Ahn et al
0,800,708	D2 D2	10/2017	Devicels at al
9,800,798	DZ	10/2017	Kavifala et al.
9,851,803	B2	12/2017	Fisher et al.
9,894,287	B2	2/2018	Oian et al.
9 900 522	B2	2/2018	Lu
0,007,600	D2 D2	2/2010	Caldenberr et el
9,927,000	BZ	3/2018	Goldenberg et al.
2002/0005902	Al	1/2002	Yuen
2002/0063711	A1	5/2002	Park et al.
2002/0075258	A1	6/2002	Park et al.
2002/0122113	A 1	0/2002	Faata
2002/0122113	AI	9/2002	
2003/0030729	AI	2/2003	Prentice et al.
2003/0093805	A1	5/2003	Gin
2003/0160886	A1	8/2003	Misawa et al.
2003/0202113	A 1	10/2003	Voshikawa
2003/0202113	A 1	1/2003	I osnikawa
2004/0008773	AI	1/2004	nokawa
2004/0017386	Al	1/2004	Liu et al.
2004/0027367	A1	2/2004	Pilu
2004/0061788	A1	4/2004	Bateman
2004/0240052	A 1	12/2004	Minofuii et al
2004/0240032	AI	1/2004	
2005/0013509	AI	1/2005	Samadani
2005/0046740	A1	3/2005	Davis
2005/0157184	A1	7/2005	Nakanishi et al.
2005/0200718	A 1	9/2005	Lee
2005/0200710	A 1	2/2005	Olson et al
2000/00/34/82	AI	3/2000	Olsell et al.
2006/0056056	AI	3/2006	Ahiska et al.
2006/0125937	A1	6/2006	LeGall et al.
2006/0170793	A1	8/2006	Pasquarette et al
2006/0175549	A 1	0.2000	
2000/01/3377		8/2006	Miller et al
2006/0197210	AI	8/2006	Miller et al.
2006/0187310	Al	8/2006 8/2006	Miller et al. Janson et al.
2006/0187310 2006/0187322	A1 A1 A1	8/2006 8/2006 8/2006	Miller et al. Janson et al. Janson et al.
2006/0187310 2006/0187322 2006/0187338	A1 A1 A1 A1	8/2006 8/2006 8/2006 8/2006	Miller et al. Janson et al. Janson et al. May et al.
2006/0187310 2006/0187322 2006/0187338 2007/0024737	A1 A1 A1 A1	8/2006 8/2006 8/2006 8/2006 2/2007	Miller et al. Janson et al. May et al. Nakamura et al
2006/0187310 2006/0187322 2006/0187338 2007/0024737	A1 A1 A1 A1 A1	8/2006 8/2006 8/2006 8/2006 2/2007 2/2007	Miller et al. Janson et al. Janson et al. May et al. Nakamura et al.
2006/0187310 2006/0187322 2006/0187338 2007/0024737 2007/0025713	A1 A1 A1 A1 A1 A1*	8/2006 8/2006 8/2006 8/2006 2/2007 2/2007	Miller et al. Janson et al. Janson et al. May et al. Nakamura et al. Hosono
2006/0187310 2006/0187322 2006/0187338 2007/0024737 2007/0025713	A1 A1 A1 A1 A1 A1*	8/2006 8/2006 8/2006 8/2006 2/2007 2/2007	Miller et al. Janson et al. Janson et al. May et al. Nakamura et al. Hosono
2006/0187310 2006/0187322 2006/0187338 2007/0024737 2007/0025713	A1 A1 A1 A1 A1 A1* A1	8/2006 8/2006 8/2006 2/2007 2/2007 8/2007	Miller et al. Janson et al. Janson et al. May et al. Nakamura et al. Hosono
2006/0187310 2006/0187322 2006/0187338 2007/0024737 2007/0025713 2007/0177025 2007/0182833	A1 A1 A1 A1 A1 A1* A1 A1*	8/2006 8/2006 8/2006 8/2006 2/2007 2/2007 8/2007 8/2007	Miller et al. Janson et al. Janson et al. May et al. Nakamura et al. Hosono
2006/0187310 2006/0187322 2006/0187338 2007/0024737 2007/0025713 2007/0177025 2007/0182833	A1 A1 A1 A1 A1 A1* A1 A1*	8/2006 8/2006 8/2006 2/2007 2/2007 8/2007 8/2007	Miller et al. Janson et al. Janson et al. Janson et al. May et al. Hosono
2006/0187310 2006/0187322 2006/0187338 2007/0024737 2007/0025713 2007/0177025 2007/0182833	Al Al Al Al Al Al Al Al Al *	8/2006 8/2006 8/2006 8/2006 2/2007 2/2007 8/2007 8/2007	Miller et al. Janson et al. Janson et al. Janson et al. May et al. Nakamura et al. Hosono 396/72 Kopet et al. Toyofuku 48/240.3
2006/0187310 2006/0187322 2006/0187338 2007/0024737 2007/0025713 2007/0177025 2007/0182833 2007/0188653	A1 A1 A1 A1 A1 A1* A1 A1* A1 A1	8/2006 8/2006 8/2006 8/2007 2/2007 2/2007 8/2007 8/2007 8/2007	Miller et al. Janson et al. Janson et al. May et al. Nakamura et al. Hosono
2006/0187310 2006/0187322 2006/0187328 2007/0024737 2007/0025713 2007/0177025 2007/0182833 2007/0188653 2007/0188653	A1 A1 A1 A1 A1 A1* A1 A1* A1 A1 A1	8/2006 8/2006 8/2006 2/2007 2/2007 8/2007 8/2007 8/2007 8/2007	Miller et al. Janson et al. Janson et al. Janson et al. May et al. Nakamura et al. Hosono
2006/0187310 2006/0187322 2006/0187338 2007/0024737 2007/0025713 2007/0177025 2007/0188653 2007/0189386 2007/0189386	A1 A1 A1 A1 A1 A1 A1 A1 A1 A1 A1 A1 A1 A	8/2006 8/2006 8/2006 2/2007 2/2007 8/2007 8/2007 8/2007 8/2007 8/2007	Miller et al. Janson et al. Janson et al. Janson et al. May et al. Nakamura et al. Hosono
2006/0187310 2006/0187322 2006/0187328 2007/0024737 2007/0025713 2007/0177025 2007/0182833 2007/0188653 2007/0188653 2007/0189386 2007/0287550	A1 A1 A1 A1 A1 A1 A1 * A1 A1 A1 A1 A1 A1 A1	8/2006 8/2006 8/2006 2/2007 2/2007 8/2007 8/2007 8/2007 8/2007 11/2007	Miller et al. Janson et al. Janson et al. Janson et al. May et al. Nakamura et al. Hosono
2006/0187310 2006/0187322 2006/0187328 2007/0024737 2007/0125713 2007/0177025 2007/0182833 2007/0188653 2007/0189386 2007/0257184 2007/0285550	A1 A1 A1 A1 A1 A1 A1 A1 A1 A1 A1 A1 A1 A	8/2006 8/2006 8/2006 2/2007 2/2007 8/2007 8/2007 8/2007 8/2007 11/2007 11/2007	Miller et al. Janson et al. Janson et al. Janson et al. May et al. Hosono
2006/0187310 2006/0187322 2006/0187338 2007/0024737 2007/0025713 2007/0177025 2007/0188653 2007/0189386 2007/0257184 2007/0255184	A1 A1 A1 A1 A1 A1 A1 A1 A1 A1 A1 A1 A1 A	8/2006 8/2006 8/2006 2/2007 2/2007 8/2007 8/2007 8/2007 8/2007 11/2007 12/2007 1/2008	Miller et al. Janson et al. Janson et al. Janson et al. May et al. Nakamura et al. Hosono
2006/0187310 2006/0187322 2006/0187328 2007/0024737 2007/0025713 2007/0177025 2007/0188653 2007/0188653 2007/0188653 2007/0189386 2007/02857184 2007/028550 2008/0017557 2008/0024614	A1 A1 A1 A1 A1 A1 A1 A1 A1 A1 A1 A1 A1 A	8/2006 8/2006 8/2006 2/2007 2/2007 8/2007 8/2007 8/2007 8/2007 8/2007 11/2007 12/2007 1/2008	Miller et al. Janson et al. Janson et al. May et al. Nakamura et al. Hosono
2006/0187310 2006/0187322 2006/0187328 2007/0024737 2007/0025713 2007/0177025 2007/0182833 2007/0188653 2007/0188653 2007/0189386 2007/0285550 2008/0017557 2008/0025634	A1 A1 A1 A1 A1 A1 A1 A1 A1 A1 A1 A1 A1 A	8/2006 8/2006 8/2006 2/2007 2/2007 8/2007 8/2007 8/2007 8/2007 11/2007 12/2007 1/2008 1/2008 1/2008	Miller et al. Janson et al. Janson et al. Janson et al. May et al. Nakamura et al. Hosono
2006/0187310 2006/0187322 2006/0187328 2007/0024737 2007/0025713 2007/0182833 2007/0188653 2007/0189386 2007/0257184 2007/0257184 2007/025550 2008/0017557 2008/0024614 2008/0025634	A1 A1 A1 A1 A1 A1 A1 A1 A1 A1 A1 A1 A1 A	8/2006 8/2006 8/2006 2/2007 2/2007 8/2007 8/2007 8/2007 8/2007 11/2007 11/2007 1/2008 1/2008 1/2008	Miller et al. Janson et al. Janson et al. Janson et al. May et al. Nakamura et al. Hosono
2006/0187310 2006/0187322 2006/0187328 2007/0024737 2007/0025713 2007/0182833 2007/0182833 2007/0188653 2007/0189386 2007/0285550 2008/0017557 2008/0024614 2008/0025634 2008/003652	Al Al Al Al Al Al Al Al Al Al Al Al Al A	8/2006 8/2006 8/2006 2/2007 2/2007 8/2007 8/2007 8/2007 8/2007 11/2007 12/2007 1/2008 1/2008 1/2008 2/2008	Miller et al. Janson et al. Janson et al. May et al. Nakamura et al. Hosono
2006/0187310 2006/0187322 2006/0187328 2007/0024737 2007/0025713 2007/0182833 2007/0188653 2007/0188653 2007/0188653 2007/0189386 2007/0285550 2008/0017557 2008/0025634 2008/0025634 2008/0030592 2008/0030611	Al Al Al Al Al Al Al Al Al Al Al Al Al A	8/2006 8/2006 8/2006 2/2007 2/2007 8/2007 8/2007 8/2007 8/2007 11/2007 12/2007 1/2008 1/2008 1/2008 2/2008	Miller et al. Janson et al. Janson et al. Janson et al. May et al. Nakamura et al. Hosono
2006/0187310 2006/0187322 2006/0187328 2007/0024737 2007/0025713 2007/0182833 2007/0188653 2007/0189386 2007/0257184 2007/0257184 2007/0257184 2007/025550 2008/0017557 2008/0024614 2008/0036592 2008/0036611 2008/00364484	AI AI AI AI AI AI AI AI AI AI AI AI AI A	8/2006 8/2006 8/2006 2/2007 2/2007 8/2007 8/2007 8/2007 8/2007 11/2007 12/2007 1/2008 1/2008 1/2008 1/2008 2/2008 4/2008	Miller et al. Janson et al. Janson et al. Janson et al. May et al. Nakamura et al. Hosono
2006/0187310 2006/0187322 2006/0187328 2007/0024737 2007/0025713 2007/0182833 2007/0182833 2007/0189386 2007/0189386 2007/028550 2008/001257184 2008/0024614 2008/0026634 2008/0030592 2008/0030592 2008/0036414 2008/0117316	AI AI AI AI AI AI AI AI AI AI AI AI AI A	8/2006 8/2006 8/2006 2/2007 2/2007 8/2007 8/2007 8/2007 8/2007 8/2007 11/2007 1/2008 1/2008 1/2008 2/2008 2/2008 4/2008	Miller et al. Janson et al. Janson et al. May et al. Nakamura et al. Hosono
2006/0187310 2006/0187322 2006/0187328 2007/0024737 2007/0025713 2007/0182833 2007/0188653 2007/0188653 2007/0188653 2007/0188653 2007/0189386 2007/0285550 2008/0017557 2008/0025634 2008/0025634 2008/0030592 2008/0030611 2008/003484 2008/00218511	A1 A1 A1 A1 A1 A1 A1 A1 A1 A1 A1 A1 A1 A	8/2006 8/2006 8/2006 2/2007 2/2007 8/2007 8/2007 8/2007 8/2007 11/2007 11/2007 1/2008 1/2008 2/2008 2/2008 2/2008 8/2008 2/2008	Miller et al. Janson et al. Janson et al. Janson et al. May et al. Nakamura et al. Hosono
2006/0187310 2006/0187322 2006/0187328 2007/0024737 2007/0025713 2007/0182833 2007/0188653 2007/0189386 2007/0189386 2007/0257184 2007/0257184 2007/0257184 2008/0025614 2008/0024614 2008/0030592 2008/0030611 2008/0036418 2008/0036418611 2008/0084484 2008/0117316 2008/0218611	A1 A1 A1 A1 A1 A1 A1 A1 A1 A1 A1 A1 A1 A	8/2006 8/2006 8/2006 2/2007 2/2007 8/2007 8/2007 8/2007 8/2007 8/2007 11/2007 12/2007 1/2008 1/2008 1/2008 2/2008 4/2008 5/2008 9/2008	Miller et al. Janson et al. Janson et al. Janson et al. May et al. Nakamura et al. Hosono
2006/0187310 2006/0187322 2006/0187328 2007/0024737 2007/0025713 2007/0182833 2007/0182833 2007/0188653 2007/0189386 2007/028550 2008/0024614 2008/0025634 2008/0026634 2008/0030592 2008/0030592 2008/003611 2008/0117316 2008/0118611 2008/0218611	A1 A1 A1 A1 A1 A1 A1 A1 A1 A1 A1 A1 A1 A	8/2006 8/2006 8/2006 2/2007 2/2007 8/2007 8/2007 8/2007 8/2007 11/2007 12/2007 1/2008 1/2008 1/2008 2/2008 2/2008 9/2008 9/2008	Miller et al. Janson et al. Janson et al. Janson et al. May et al. Nakamura et al. Hosono
2006/0187310 2006/0187322 2006/0187328 2007/0024737 2007/0025713 2007/0182833 2007/0188653 2007/0188653 2007/0188653 2007/0188653 2007/0285550 2008/0017557 2008/0025634 2008/0025634 2008/0025634 2008/0025634 2008/0030592 2008/0030592 2008/0030611 2008/0218611 2008/0218612 2008/0218613	A1 A1 A1 A1 A1 A1 A1 A1 A1 A1 A1 A1 A1 A	8/2006 8/2006 8/2006 2/2007 2/2007 8/2007 8/2007 8/2007 8/2007 1/2008 1/2008 1/2008 1/2008 2/2008 2/2008 2/2008 9/2008 9/2008	Miller et al. Janson et al. Janson et al. Janson et al. May et al. Nakamura et al. Hosono
2006/0187310 2006/0187322 2006/0187328 2007/0024737 2007/0025713 2007/0182833 2007/0188653 2007/0189386 2007/0189386 2007/0257184 2007/0257184 2007/0257184 2007/025550 2008/0017557 2008/0025634 2008/0030592 2008/0030611 2008/003048484 2008/0117316 2008/0218611 2008/0218611 2008/0218613 2008/0219654	A1 A1 A1 A1 A1 A1 A1 A1 A1 A1 A1 A1 A1 A	8/2006 8/2006 8/2006 2/2007 2/2007 8/2007 8/2007 8/2007 8/2007 8/2007 1/2008 1/2008 1/2008 1/2008 2/2008 4/2008 9/2008 9/2008 9/2008	Miller et al. Janson et al. Janson et al. Janson et al. May et al. Nakamura et al. Hosono
2006/0187310 2006/0187322 2006/0187328 2007/0024737 2007/0025713 2007/0182833 2007/0182833 2007/0189386 2007/0189386 2007/028550 2008/0024614 2008/0025634 2008/0030592 2008/0030611 2008/0034841 2008/0218611 2008/0218613 2008/0218613 2008/0218613 2008/0218613	A1 A1 A1 A1 A1 A1 A1 A1 A1 A1 A1 A1 A1 A	8/2006 8/2006 8/2006 2/2007 2/2007 8/2007 8/2007 8/2007 8/2007 11/2007 11/2007 1/2008 1/2008 1/2008 2/2008 9/2008 9/2008 9/2008 9/2008	Miller et al. Janson et al. Janson et al. Janson et al. May et al. Nakamura et al. Hosono
2006/0187310 2006/0187322 2006/0187328 2007/0024737 2007/0025713 2007/0182833 2007/0188653 2007/0188653 2007/0188653 2007/0189386 2007/0285550 2008/0017557 2008/0025634 2008/0025634 2008/0025634 2008/0026634 2008/0218611 2008/0218611 2008/0218613 2008/0218613 2008/0218643	AI AI AI AI AI AI AI AI AI AI AI AI AI A	8/2006 8/2006 8/2006 2/2007 2/2007 8/2007 8/2007 8/2007 1/2007 1/2007 1/2007 1/2008 1/2008 2/2008 2/2008 2/2008 2/2008 2/2008 2/2008 2/2008 2/2008 2/2008 2/2007 1/2008 2/2007 1/2008 1/2008 2/2008 2/2008 9/2008 9/2008 9/2008 9/2008 1/2008	Miller et al. Janson et al. Janson et al. Janson et al. May et al. Nakamura et al. Hosono

(56)**References** Cited

U.S. PATENT DOCUMENTS

2000/0122406	A 1	5/2000	Rouvinen et al
2009/0122400	AI	5/2009	Kouvinen et al.
2009/0128644	AI	5/2009	Camp et al.
2009/0219547	A1	9/2009	Kauhanen et al.
2000/0252484	A 1	10/2000	Hasuda et al
2000/0202404	7 1 1	10/2009	
2009/0295949	AI	12/2009	Ojala
2010/0013906	A1	1/2010	Border et al.
2010/0020221	Δ1	1/2010	Tupman et al
2010/0020221	111	2/2010	
2010/0000/40	A9	3/2010	Olsen et al.
2010/0103194	A1	4/2010	Chen et al.
2010/0238327	A 1	9/2010	Griffith et al
2010/0277610	A 1 *	11/2010	Sourff HOAN 5/2259
2010/02//019	AI '	11/2010	Scarii 1041 3/2238
			348/240.1
2010/0283842	A 1	11/2010	Guissin et al
2010/0203012	A 1	2/2011	De alt an et al
2011/0004327	AI	3/2011	Dagner et al.
2011/0080487	Al	4/2011	Venkataraman et al.
2011/0128288	A1	6/2011	Petrou et al.
2011/0164172	A 1	7/2011	Shintoni et al
2011/0104172	AL	7/2011	Similari et al.
2011/0229054	AI	9/2011	weston et al.
2011/0234853	A1	9/2011	Hayashi et al.
2011/0234881	A1	9/2011	Wakabayashi et al
2011/02/2286	A 1	10/2011	Page et el
2011/0242280	AI	10/2011	race et al.
2011/0242355	Al	10/2011	Goma et al.
2012/0026366	A1	2/2012	Golan et al.
2012/0062780	Δ1	3/2012	Morihisa
2012/0002700	A 1	2/2012	In the second se
2012/0009235	AI	3/2012	Imai
2012/0075489	A1	3/2012	Nishihara
2012/0105579	A1	5/2012	Jeon et al.
2012/0106648	A 1	8/2012	Havens et al
2012/01/0040	AI 41	0/2012	
2012/0229003	AI	9/2012	Nelson et al.
2012/0249815	A1	10/2012	Bohn et al.
2012/0287315	A1	11/2012	Huang et al.
2012/0320467	A 1	12/2012	Baik et al
2012/0520407	A 1	1/2012	Daik et al.
2013/0002928	AI	1/2013	Imai
2013/0093842	Al	4/2013	Yahata
2013/0135445	A1	5/2013	Dahi et al.
2013/0182150	A 1	7/2013	Acalura
2013/0102130	A1	0/2013	A sakula
2013/0201360	AI	8/2013	Song
2013/0202273	Al	8/2013	Ouedraogo et al.
2013/0235224	A1	9/2013	Park et al.
2013/0250150	A 1	0/2013	Malone et al
2012/0250150	A 1	10/2012	Datta LaCrain
2015/0258044	AI	10/2013	Beus-LaCroix
2013/0321668	A1	12/2013	Kamath
2014/0049615	A1	2/2014	Uwagawa
2014/0118584	Δ1	5/2014	Lee et al
2014/0102229	A 1	7/2014	Atten et el
2014/0192238	AI	7/2014	Attar et al.
2014/0192253	Al	7/2014	Laroia
2014/0253693	A1*	9/2014	Shikata
			248/47
2014/02/7024	4 1 *	0/2014	546/47
2014/026/834	AI*	9/2014	Aoki H04N 5/23296
			348/240.1
2014/0313316	A1	10/2014	Olsson et al.
2011/0262242	A 1	10/2011	Talizarua
2014/0302242	AI	12/2014	Takizawa
2015/0002683	Al	1/2015	Hu et al.
2015/0042870	A1	2/2015	Chan et al.
2015/0085174	A 1 *	3/2015	Shabtay H04N 5/23206
2015/0085174	AI	5/2015	Shabtay 11041 3/23230
			348/336
2015/0092066	A1	4/2015	Geiss et al.
2015/0154776	Δ1	6/2015	Zhang et al
2015/0162049	A 1	6/2015	Hirata at al
2013/0102048	AL	0/2015	
2015/0195458		-7/2015	Nakayama et al.
2015/0215516	Al	1	
2015/0215516	Al Al	7/2015	Dolgin
2015/0215516	Al Al Al	7/2015	Dolgin Choi et al
2015/0215516 2015/0237280	Al Al Al	7/2015 8/2015	Dolgin Choi et al.
2015/0215516 2015/0237280 2015/0242994	Al Al Al Al	7/2015 8/2015 8/2015	Dolgin Choi et al. Shen
2015/0215516 2015/0237280 2015/0242994 2015/0271471	A1 A1 A1 A1 A1 A1	7/2015 8/2015 8/2015 9/2015	Dolgin Choi et al. Shen Hsieh et al.
2015/0215516 2015/0237280 2015/0242994 2015/0271471 2015/0316744	A1 A1 A1 A1 A1 A1	7/2015 8/2015 8/2015 9/2015 11/2015	Dolgin Choi et al. Shen Hsieh et al. Chen
2015/0215516 2015/0237280 2015/0242994 2015/0271471 2015/0316744 2015/0224200	A1 A1 A1 A1 A1 A1	7/2015 8/2015 8/2015 9/2015 11/2015	Dolgin Choi et al. Shen Hsieh et al. Chen
2015/0215516 2015/0237280 2015/0242994 2015/0271471 2015/0316744 2015/0334309	A1 A1 A1 A1 A1 A1 A1 A1	7/2015 8/2015 8/2015 9/2015 11/2015 11/2015	Dolgin Choi et al. Shen Hsieh et al. Chen Peng et al.
2015/0215516 2015/0237280 2015/0242994 2015/0271471 2015/0316744 2015/0334309 2016/0044250	A1 A1 A1 A1 A1 A1 A1 A1 A1	7/2015 8/2015 8/2015 9/2015 11/2015 11/2015 2/2016	Dolgin Choi et al. Shen Hsieh et al. Chen Peng et al. Shabtay et al.
2015/0215516 2015/0237280 2015/0242994 2015/0271471 2015/0316744 2015/0334309 2016/0044250 2016/0070088	A1 A1 A1 A1 A1 A1 A1 A1 A1 A1	7/2015 8/2015 8/2015 9/2015 11/2015 11/2015 2/2016 3/2016	Dolgin Choi et al. Shen Hsieh et al. Chen Peng et al. Shabtay et al. Koguchi
2015/0215516 2015/0237280 2015/0242994 2015/0271471 2015/0316744 2015/0334309 2016/0044250 2016/0070088	A1 A1 A1 A1 A1 A1 A1 A1 A1 A1	7/2015 8/2015 8/2015 9/2015 11/2015 11/2015 2/2016 3/2016	Dolgin Choi et al. Shen Hsieh et al. Chen Peng et al. Shabtay et al. Koguchi
2015/0215516 2015/0237280 2015/0242994 2015/0271471 2015/0316744 2015/0334309 2016/0044250 2016/0070088 2016/0154202	A1 A1 A1 A1 A1 A1 A1 A1 A1 A1 A1	7/2015 8/2015 8/2015 9/2015 11/2015 11/2015 2/2016 3/2016 6/2016	Dolgin Choi et al. Shen Hsieh et al. Chen Peng et al. Shabtay et al. Koguchi Wippermann et al.

2016/0212358	A1 7/2016	Shikata
2016/0241793	A1* 8/2016	Ravirala H04N 5/247
2016/0301840	A1 10/2016	Du et al.
2016/0353012	A1 12/2016	Kao et al.
2017/0019616	A1 1/2017	Zhu et al.
2017/0214846	A1 7/2017	Du et al.
2017/0214866	A 1 7/2017	Zhu et al.
2017/0289458	A1 10/2017	Song et al.
2018/0120674	A1 5/2018	Avivi et al.
2018/0150973	A1 5/2018	Tang et al.
2018/0241922	A1 8/2018	Baldwin et al.
2018/0295292	A1 10/2018	Lee et al.

FOREIGN PATENT DOCUMENTS

CN	103024272	Α	4/2013	
EP	1536633	A1	6/2005	
EP	2523450	A1	11/2012	
JP	04211230	Α	8/1992	
JP	H07318864	Α	12/1995	
JP	08271976	Α	10/1996	
JP	2003298920	Α	10/2003	
JP	2004133054	Α	4/2004	
JP	2005099265	Α	4/2005	
JP	2006238325	Α	9/2006	
JP	2007228006	Α	9/2007	
JP	2007306282	Α	11/2007	
JP	2008076485	Α	4/2008	
JP	2013106289	Α	5/2013	
KR	20100008936	Α	1/2010	
KR	20140014787	Α	2/2014	
KR	101477178	B1	12/2014	
WO	WO-2014199338	A2	* 12/2014	H04N 5/2258

OTHER PUBLICATIONS

A 3MPixel Multi-Aperture Image Sensor with 0.7µm Pixels in 0.11µm CMOS, Fife et al., Stanford University, 2008, 3 pages.

Dual camera intelligent sensor for high definition 360 degrees surveillance, Scotti et al., Publisher: IET, May 9, 2000, 8 pages. Dual-sensor foveated imaging system, Hua et al., Publisher: Optical

Society of America, Jan. 14, 2008, 11 pages. Defocus Video Matting, McGuire et al., Publisher: ACM SIG-GRAPH, Jul. 31, 2005, 11 pages.

Compact multi-aperture imaging with high angular resolution, Santacana et al., Publisher: Optical Society of America, 2015, 10 pages.

Multi-Aperture Photography, Green et al., Publisher: Mitsubishi Electric Research Laboratories, Inc., Jul. 2007, 10 pages.

Multispectral Bilateral Video Fusion, Bennett et al., Publisher: IEEE, May 2007, 10 pages.

Super-resolution imaging using a camera array, Santacana et al., Publisher: Optical Society of America, 2014, 6 pages

Optical Splitting Trees for High-Precision Monocular Imaging, McGuire et al., Publisher: IEEE, 2007, 11 pages.

High Performance Imaging Using Large Camera Arrays, Wilburn et al., Publisher: Association for Computing Machinery, Inc., 2005, 12 pages.

Real-time Edge-Aware Image Processing with the Bilateral Grid, Chen et al., Publisher: ACM SIGGRAPH, 2007, 9 pages.

Superimposed multi-resolution imaging, Carles et al., Publisher: Optical Society of America, 2017, 13 pages.

Viewfinder Alignment, Adams et al., Publisher: Eurographics, 2008, 10 pages.

Dual-Camera System for Multi-Level Activity Recognition, Bodor et al., Publisher: IEEE, Oct. 2014, 6 pages.

Engineered to the task: Why camera-phone cameras are different, Giles Humpston, Publisher: Solid State Technology, Jun. 2009, 3 pages.

* cited by examiner













FIG. 2







FIG. 3B



FIG. 3C



FIG. 4

20

DUAL APERTURE ZOOM CAMERA WITH VIDEO SUPPORT AND SWITCHING / NON-SWITCHING DYNAMIC CONTROL

CROSS REFERENCE TO RELATED APPLICATIONS

This application is a continuation of U.S. patent application Ser. No. 15/324,720 filed Jan. 8, 2017 (now allowed), which was a 371 application from international patent ¹⁰ application PCT/IB2016/053803 filed Jun. 26, 2016, and is related to and claims priority from U.S. Provisional Patent Application No. 62/204,667 filed Aug. 13, 2015 which is expressly incorporated herein by reference in its entirety.

FIELD

Embodiments disclosed herein relate in general to digital cameras and in particular to zoom digital cameras with video capabilities.

BACKGROUND

Digital camera modules are currently being incorporated into a variety of host devices. Such host devices include 25 cellular telephones, personal data assistants (PDAs), computers, and so forth. Consumer demand for digital camera modules in host devices continues to grow.

Host device manufacturers prefer digital camera modules to be small, so that they can be incorporated into the host 30 device without increasing its overall size. Further, there is an increasing demand for such cameras to have higher-performance characteristics. One such characteristic possessed by many higher-performance cameras (e.g., standalone digital still cameras) is the ability to vary the focal length of the 35 camera to increase and decrease the magnification of the image. This ability, typically accomplished with a zoom lens, is known as optical zooming. "Zoom" is commonly understood as a capability to provide different magnifications of the same scene and/or object by changing the focal 40 length of an optical system, with a higher level of zoom associated with greater magnification and a lower level of zoom associated with lower magnification. Optical zooming is typically accomplished by mechanically moving lens elements relative to each other. Such zoom lenses are 45 typically more expensive, larger and less reliable than fixed focal length lenses. An alternative approach for approximating the zoom effect is achieved with what is known as digital zooming. With digital zooming, instead of varying the focal length of the lens, a processor in the camera crops the image 50 and interpolates between the pixels of the captured image to create a magnified but lower-resolution image.

Attempts to use multi-aperture imaging systems to approximate the effect of a zoom lens are known. A multiaperture imaging system (implemented for example in a 55 digital camera) includes a plurality of optical sub-systems (also referred to as "cameras"). Each camera includes one or more lenses and/or other optical elements which define an aperture such that received electro-magnetic radiation is imaged by the optical sub-system and a resulting image is 60 directed towards a two-dimensional (2D) pixelated image sensor region. The image sensor (or simply "sensor") region is configured to receive the image and to generate a set of image data based on the image. The digital camera may be aligned to receive electromagnetic radiation associated with 65 scenery having a given set of one or more objects. The set of image data may be represented as digital image data, as

well known in the art. Hereinafter in this description, "image" "image data" and "digital image data" may be used interchangeably. Also, "object" and "scene" may be used interchangeably. As used herein, the term "object" is an entity in the real world imaged to a point or pixel in the image.

Multi-aperture imaging systems and associated methods are described for example in US Patent Publications No. 2008/0030592, 2010/0277619 and 2011/0064327. In US 2008/0030592, two sensors are operated simultaneously to capture an image imaged through an associated lens. A sensor and its associated lens form a lens/sensor combination. The two lenses have different focal lengths. Thus, even though each lens/sensor combination is aligned to look in the same direction, each combination captures an image of the same subject but with two different fields of view (FOV). One sensor is commonly called "Wide" and the other "Tele". Each sensor provides a separate image, referred to respectively as "Wide" (or "W") and "Tele" (or "T") images. A W-image reflects a wider FOV and has lower resolution than the T-image. The images are then stitched (fused) together to form a composite ("fused") image. In the composite image, the central portion is formed by the relatively higherresolution image taken by the lens/sensor combination with the longer focal length, and the peripheral portion is formed by a peripheral portion of the relatively lower-resolution image taken by the lens/sensor combination with the shorter focal length. The user selects a desired amount of zoom and the composite image is used to interpolate values from the chosen amount of zoom to provide a respective zoom image. The solution offered by US 2008/0030592 requires, in video mode, very large processing resources in addition to high frame rate requirements and high power consumption (since both cameras are fully operational).

US 2010/0277619 teaches a camera with two lens/sensor combinations, the two lenses having different focal lengths, so that the image from one of the combinations has a FOV approximately 2-3 times greater than the image from the other combination. As a user of the camera requests a given amount of zoom, the zoomed image is provided from the lens/sensor combination having a FOV that is next larger than the requested FOV. Thus, if the requested FOV is less than the smaller FOV combination, the zoomed image is created from the image captured by that combination, using cropping and interpolation if necessary. Similarly, if the requested FOV is greater than the smaller FOV combination, the zoomed image is created from the image captured by the other combination, using cropping and interpolation if necessary. The solution offered by US 2010/0277619 leads to parallax artifacts when moving to the Tele camera in video mode.

In both US 2008/0030592 and US 2010/0277619, different focal length systems cause matching Tele and Wide FOVs to be exposed at different times using CMOS sensors. This degrades the overall image quality. Different optical F numbers ("F#") cause image intensity differences. Working with such a dual sensor system requires double bandwidth support, i.e. additional wires from the sensors to the following HW component. Neither US 2008/0030592 nor US 2010/0277619 deal with registration errors.

US 2011/0064327 discloses multi-aperture imaging systems and methods for image data fusion that include providing first and second sets of image data corresponding to an imaged first and second scene respectively. The scenes overlap at least partially in an overlap region, defining a first collection of overlap image data as part of the first set of image data, and a second collection of overlap image data as

25

part of the second set of image data. The second collection of overlap image data is represented as a plurality of image data cameras such that each of the cameras is based on at least one characteristic of the second collection, and each camera spans the overlap region. A fused set of image data 5 is produced by an image processor, by modifying the first collection of overlap image data based on at least a selected one of, but less than all of, the image data cameras. The systems and methods disclosed in this application deal solely with fused still images.

None of the known art references provide a thin (e.g. fitting in a cell-phone) dual-aperture zoom digital camera with fixed focal length lenses, the camera configured to operate in both still mode and video mode to provide still and video images, wherein the camera configuration does 15 not use any fusion to provide a continuous, smooth zoom in video mode.

Therefore there is a need for, and it would be advantageous to have thin digital cameras with optical zoom operating in both video and still mode that do not suffer from 20 commonly encountered problems and disadvantages, some of which are listed above.

SUMMARY

Embodiments disclosed herein teach the use of dualaperture (also referred to as dual-lens or two-sensor) optical zoom digital cameras. The cameras include two cameras, a Wide camera and a Tele camera, each camera including a fixed focal length lens, an image sensor and an image signal 30 processor (ISP). The Tele camera is the higher zoom camera and the Wide camera is the lower zoom camera. In some embodiments, the thickness/effective focal length (EFL) ratio of the Tele lens is smaller than about 1. The image sensor may include two separate 2D pixelated sensors or a 35 single pixelated sensor divided into at least two areas. The digital camera can be operated in both still and video modes. In video mode, optical zoom is achieved "without fusion", by, in some embodiments, switching between the W and T images to shorten computational time requirements, thus 40 enabling high video rate. To avoid discontinuities in video mode, the switching includes applying additional processing blocks, which include in some embodiments image scaling and shifting. In some embodiments, when a no-switching criterion is fulfilled, optical zoom is achieved in video mode 45 without switching.

As used herein, the term "video" refers to any camera output that captures motion by a series of pictures (images), as opposed to "still mode" that friezes motion. Examples of "video" in cellphones and smartphones include "video 50 mode" or "preview mode".

In order to reach optical zoom capabilities, a different magnification image of the same scene is captured (grabbed) by each camera, resulting in FOV overlap between the two cameras. Processing is applied on the two images to fuse and 55 output one fused image in still mode. The fused image is processed according to a user zoom factor request. As part of the fusion procedure, up-sampling may be applied on one or both of the grabbed images to scale it to the image grabbed by the Tele camera or to a scale defined by the user. 60 The fusion or up-sampling may be applied to only some of the pixels of a sensor. Down-sampling can be performed as well if the output resolution is smaller than the sensor resolution.

The cameras and associated methods disclosed herein 65 address and correct many of the problems and disadvantages of known dual-aperture optical zoom digital cameras. They

4

provide an overall zoom solution that refers to all aspects: optics, algorithmic processing and system hardware (HW).

In a dual-aperture camera image plane, as seen by each camera (and respective image sensor), a given object will be shifted and have different perspective (shape). This is referred to as point-of-view (POV). The system output image can have the shape and position of either camera image or the shape or position of a combination thereof. If the output image retains the Wide image shape then it has the Wide perspective POV. If it retains the Wide camera position then it has the Wide position POV. The same applies for Tele images position and perspective. As used in this description, the perspective POV may be of the Wide or Tele cameras, while the position POV may shift continuously between the Wide and Tele cameras. In fused images, it is possible to register Tele image pixels to a matching pixel set within the Wide image pixels, in which case the output image will retain the Wide POV ("Wide fusion"). Alternatively, it is possible to register Wide image pixels to a matching pixel set within the Tele image pixels, in which case the output image will retain the Tele POV ("Tele fusion"). It is also possible to perform the registration after either camera image is shifted, in which case the output image will retain the respective Wide or Tele perspective POV.

In an exemplary embodiment, there is provided a zoom digital camera comprising a Wide imaging section that includes a fixed focal length Wide lens with a Wide FOV and a Wide sensor, the Wide imaging section operative to provide Wide image data of an object or scene, a Tele imaging section that includes a fixed focal length Tele lens with a Tele FOV that is narrower than the Wide FOV and a Tele sensor, the Tele imaging section operative to provide Tele image data of the object or scene, and a camera controller operatively coupled to the Wide and Tele imaging sections, the camera controller configured to evaluate a no-switching criterion determined by inputs from both Wide and Tele image data, and, if the no-switching criterion is fulfilled, to output a zoom video output image that includes only Wide image data in a zoom-in operation between a lower zoom factor (ZF) value and a higher ZF value.

In an exemplary embodiment there is provided a method for obtaining zoom images of an object or scene using a digital camera, comprising the steps of providing in the digital camera a Wide imaging section having a Wide lens with a Wide FOV and a Wide sensor, a Tele imaging section having a Tele lens with a Tele FOV that is narrower than the Wide FOV and a Tele sensor, and a camera controller operatively coupled to the Wide and Tele imaging sections, and configuring the camera controller to evaluate a noswitching criterion determined by inputs from both Wide and Tele image data, and, if the no-switching criterion is fulfilled, to output a zoom video output image that includes only Wide image data in a zoom-in operation between a lower ZF value and a higher ZF value.

In some exemplary embodiments, the no-switching criterion includes a shift between the Wide and Tele images calculated by global registration, the shift being greater than a first threshold.

In some exemplary embodiments, the no-switching criterion includes a disparity range calculated by global registration, the disparity range being greater than a second threshold.

In some exemplary embodiments, the no-switching criterion includes an effective resolution of the Tele image being lower than an effective resolution of the Wide image.

65

In some exemplary embodiments, the no-switching criterion includes a number of corresponding features in the Wide and Tele images being smaller than a third threshold.

In some exemplary embodiments, the no-switching criterion includes a majority of objects imaged in an overlap area of the Wide and Tele images being calculated to be closer to the camera than a first threshold distance.

In some exemplary embodiments, the no-switching criterion includes some objects imaged in an overlap area of the Wide and Tele images being calculated to be closer than a second threshold distance while other objects imaged in the overlap area of the Wide and Tele images being calculated to be farther than a third distance threshold.

In some exemplary embodiments, the camera controller includes a user control module for receiving user inputs and a sensor control module for configuring each sensor to acquire the Wide and Tele image data based on the user inputs.

In some exemplary embodiments, the user inputs include 20 a zoom factor, a camera mode and a region of interest.

In some exemplary embodiments, the Tele lens includes a ratio of total track length (TTL)/effective focal length (EFL) smaller than 1. For a definition of TTL and EFL see e.g. co-assigned US published patent application No. 25 20150244942.

In some exemplary embodiments, if the no-switching criterion is not fulfilled, the camera controller is further configured to output video output images with a smooth transition when switching between the lower ZF value and the higher ZF value or vice versa, wherein at the lower ZF value the output image is determined by the Wide sensor, and wherein at the higher ZF value the output image is determined by the Tele sensor.

In some exemplary embodiments, the camera controller is further configured to combine in still mode, at a predefined range of ZF values, at least some of the Wide and Tele image data to provide a fused output image of the object or scene from a particular point of view.

BRIEF DESCRIPTION OF THE DRAWINGS

Non-limiting examples of embodiments disclosed herein are described below with reference to figures attached hereto 45 that are listed following this paragraph. Identical structures, elements or parts that appear in more than one figure are generally labeled with a same numeral in all the figures in which they appear. The drawings and descriptions are meant to illuminate and clarify embodiments disclosed herein, and 50 should not be considered limiting in any way.

FIG. 1A shows schematically a block diagram illustrating an exemplary dual-aperture zoom imaging system disclosed herein;

FIG. 1B is a schematic mechanical diagram of the dualaperture zoom imaging system of FIG. 1A:

FIG. 2 shows an example of a Wide sensor, a Tele sensor and their respective FOVs;

FIG. 3A shows an embodiment of an exemplary method $_{60}$ disclosed herein for acquiring a zoom image in video/ preview mode;

FIG. 3B shows exemplary feature points in an object;

FIG. 3C shows schematically a known rectification process:

FIG. 4 shows a graph illustrating an effective resolution zoom factor.

DETAILED DESCRIPTION

Definitions

Sharpness score: the gradients (dx, dy) of the image are compared (through subtraction) to the gradients of its low pass filtered version. A higher difference indicates a sharper original image. The result of this comparison is normalized with respect to the average variations (for example, sum of absolute gradients) of the original image, to obtain an absolute sharpness score.

Edge score: for each image, the edges are found (for example, using Canny edge detection) and the average intensity of gradients along them is calculated, for example, by calculating the magnitude of gradients (dx, dy) for each edge pixel, summing the results and dividing by the total number of edge pixels. The result is the edge score.

Effective resolution score: this score is calculated only in a region of interest (ROI) and provides a good indication of the effective resolution level in the image. As used herein, "ROI" is a user-defined sub-region of the image that may be exemplarily 4% or less of the image area. The effective resolution score can be derived from a combination of the sharpness scores and edge scores for each image, for example by normalizing both to be between [0, 1] and by taking their average.

FIG. 1A shows schematically a block diagram illustrating an exemplary embodiment of a dual-aperture zoom imaging system (also referred to simply as "dual-camera" or "dualaperture camera") disclosed herein and numbered 100. Dual-aperture camera 100 comprises a Wide imaging section ("Wide camera") that includes a Wide lens block 102, a Wide image sensor 104 and a Wide image processor 106. Dual-aperture camera 100 further comprises a Tele imaging section ("Tele camera") that includes a Tele lens block 108, a Tele image sensor 110 and a Tele image processor 112. The image sensors may be physically separate or may be part of a single larger image sensor. The Wide sensor pixel size can be equal to or different from the Tele sensor pixel size. 40 Dual-aperture camera 100 further comprises a camera fusion processing core (also referred to as "controller") 114 that includes a sensor control module 116, a user control module 118, a video processing module 126 and a capture processing module 128, all operationally coupled to sensor control block 110. User control module 118 comprises an operational mode function 120, a ROI function 122 and a zoom factor (ZF) function 124.

Sensor control module 116 is connected to the two (Wide and Tele) cameras and to the user control module 118 and used to choose, according to the zoom factor, which of the sensors is operational and to control the exposure mechanism and the sensor readout. Mode choice function 120 is used for choosing capture/video modes. ROI function 122 is used to choose a region of interest. The ROI is the region on which both cameras are focused on. Zoom factor function 124 is used to choose a zoom factor. Video processing module 126 is connected to mode choice function 120 and used for video processing. It is configurable to evaluate a no-switching criterion determined by inputs from both Wide and Tele image data and to make a decision regarding video output. Specifically, upon evaluation of a no-switching criterion, if the no-switching criterion is fulfilled, module 126 is configurable to output a zoom video output image that includes only Wide image data in a zoom-in operation between a lower zoom factor (ZF) value and a higher ZF value. If the no-switching criterion is not fulfilled, module 126 is configurable to combine in still mode, at a predefined

range of ZF values, at least some of the Wide and Tele image data to provide a fused output image of the object or scene from a particular point of view. Still processing module **128** is connected to the mode choice function **120** and used for high image quality still mode images. The video processing 5 module is applied when the user desires to shoot in video mode. The capture processing module is applied when the user wishes to shoot still pictures.

FIG. 1B is a schematic mechanical diagram of the dualaperture zoom imaging system of FIG. 1A. Exemplary 10 dimensions: Wide lens TTL=4.2 mm and EFL=3.5 mm; Tele lens TTL=6 mm and EFL=7 mm; both Wide and Tele sensors $\frac{1}{3}$ inch; external dimensions of Wide and Tele cameras: width (w) and length (1)=8.5 mm and height (h)=6.8 mm; distance "d" between camera centers=10 mm. 15

Following is a detailed description and examples of different methods of use of dual-aperture camera **100**. Still Mode Operation/Function

In still camera mode, the obtained image is fused from information obtained by both cameras at all zoom levels, see 20 FIG. 2, which shows a Wide sensor 202 and a Tele sensor **204** and their respective FOVs. Exemplarily, as shown, the Tele sensor FOV is half the Wide sensor FOV. The still camera mode processing includes two stages: the first stage includes setting HW settings and configuration, where a first 25 objective is to control the sensors in such a way that matching FOVs in both images (Tele and Wide) are scanned at the same time, a second objective is to control the relative exposures according to the lens properties, and a third objective is to minimize the required bandwidth from both 30 sensors for the ISPs. The second stage includes image processing that fuses the Wide and the Tele images to achieve optical zoom, improves SNR and provides wide dynamic range.

FIG. **3**A shows image line numbers vs. time for an image 35 section captured by CMOS sensors. A fused image is obtained by line (row) scans of each image. To prevent matching FOVs in both sensors to be scanned at different times, a particular configuration is applied by the camera controller on both image sensors while keeping the same 40 frame rate. The difference in FOV between the sensors determines the relationship between the rolling shutter time and the vertical blanking time for each sensor.

Video Mode Operation/Function

Smooth Transition

When a dual-aperture camera switches the camera output between cameras or points of view, a user will normally see a "jump" (discontinuous) image change. However, a change in the zoom factor for the same camera and POV is viewed as a continuous change. A "smooth transition" (ST) is a 50 transition between cameras or POVs that minimizes the jump effect. This may include matching the position, scale, brightness and color of the output image before and after the transition. However, an entire image position matching between the camera outputs is in many cases impossible, 55 because parallax causes the position shift to be dependent on the object distance. Therefore, in a smooth transition as disclosed herein, the position matching is achieved only in the ROI region while scale brightness and color are matched for the entire output image area. 60

Zoom-in and Zoom-Out in Video Mode

In video mode, sensor oversampling is used to enable continuous and smooth zoom experience. Processing is applied to eliminate the changes in the image during cross-over from one camera to the other. Zoom from 1 to Z_{switch} 65 is performed using the Wide sensor only. From Z_{switch} and on, it is performed mainly by the Tele sensor. To prevent

8

"jumps" (roughness in the image), switching to the Tele image is done using a zoom factor which is a bit higher ($Z_{switch}+\Delta Zoom$) than Z_{switch} . $\Delta Zoom$ is determined according to the system's properties and is different for cases where zoom-in is applied and cases where zoom-out is applied ($\Delta Zoom_{in}$, $\Delta Zoom_{out}$). This is done to prevent residual jumps artifacts to be visible at a certain zoom factor. The switching between sensors, for an increasing zoom and for decreasing zoom, is done on a different zoom factor.

The zoom video mode operation includes two stages: (1) sensor control and configuration and (2) image processing. In the range from 1 to Z_{switch} , only the Wide sensor is operational, hence, power can be supplied only to this sensor. Similar conditions hold for a Wide AF mechanism. From $Z_{switch}+\Delta Zoom$ to Z_{max} only the Tele sensor is operational, hence, power is supplied only to this sensor. Similarly, only the Tele sensor is operational and power is supplied only to it for a Tele AF mechanism. Another option is that the Tele sensor is operational and the Wide sensor is working in low frame rate. From Z_{switch} to $Z_{switch}+\Delta Zoom$, both sensors are operational.

Zoom-in:

45

at low ZF up to slightly above ZF_T (the zoom factor that enables switching between Wide and Tele outputs) the output image is the digitally zoomed, unchanged Wide camera output. ZF_T is defined as follows:

$ZF_T = Tan(FOV_{Wide})/Tan(FOV_{Tele})$

where Tan refers to "tangent", while FOV_{*Wide*} and FOV_{*Tele*} refer respectively to the Wide and Tele lens fields of view (in degrees). As used herein, the FOV is measured from the center axis to the corner of the sensor (i.e. half the angle of the normal definition). Switching cannot take place below ZF_T and it can above it.

In some embodiments for the up-transfer ZF, as disclosed in co-invented and co-owned U.S. Pat. No. 9,185,291, the output is a transformed Tele camera output, where the transformation is performed by a global registration (GR) algorithm to achieve smooth transition. As used herein "global registration" refers to an action for which the inputs are the Wide and Tele images. The Wide image is cropped to display the same FOV as the Tele image. The Tele image is passed through a low pass filter (LPF) and resized to make its appearance as close as possible to the Wide image (lower resolution and same pixel count). The outputs of GR are corresponding feature point pairs in the images along with their disparities, and parameters for differences between the images, i.e. shift and scale. As used herein, "feature point" refers to a point such as points 10a-d in FIG. 3B and refers to a point (pixel) of interest on an object in an image. For purposes set forth in this description, a feature point should be reproducible and invariant to changes in image scale, noise and illumination. Such points usually lie on corners or other high-contrast regions of the object.

Stages of Global Registration

In some exemplary embodiments, global registration may be performed as follows:

 Find interest points (features) in each image separately by filtering it with, exemplarily, a Difference of Gaussians filter,
and finding local extrema on the resulting image.

2. Find feature correspondences (features in both images that describe the same point in space) in a "matching" process. These are also referred to as "feature pairs", "correspondence pairs" or "matching pairs". This is done by comparing each feature point from one (Tele or Wide) image (referred to hereinafter as "image 1") to all feature points in that region from the other (respectively Wide or Tele) image

35

45

(referred to hereinafter as "image 2"). The features are compared only within their group of minima/maxima, using patch normalized cross-correlation. As used herein, "patch" refers to a group of neighboring pixels around an origin pixel.

3. The normalized cross correlation of two image patches t(x,y) and f(x,y) is

$$\frac{1}{n} \sum_{x,y} \frac{(f(x, y) - \overline{f})(t(x, y) - \overline{t})}{\sigma_f \sigma_t}$$

where n is the number of pixels in both patches, \tilde{T} is the average of f and σ_f is the standard deviation of f. A match for a feature point from image 1 is only confirmed if its correlation score is much higher (for example, x1.2) than the next-best matching feature from image 2.

4. Find the disparity between each pair of corresponding features (also referred to as "matching pair") by subtracting their x and y coordinate values.

5. Filter bad matching points:

a. Following the matching process, matches that include feature points from image 2 that were matched to more than one feature from image 1 are discarded.

b. Matching pairs whose disparity is inconsistent with the other matching pairs are discarded. For example, if there is one corresponding pair which whose disparity is lower or higher than the others by 20 pixels.

6. The localization accuracy for matched points from image 2 is refined by calculating a correlation of neighboring pixel patches from image 2 with the target patch (the patch around the current pixel (of the current matching pair) from image 1, modeling the results as a parabola and finding its maximum.

7. Rotation and fine scale differences are calculated between the two images according to the matching points (for example, by subtracting the center of mass from each set of points, i.e. the part of the matching points belonging to either the Wide or the Tele image, and solving a least squares problem).

8. After compensating for these differences, since the images were rectified, the disparity in the Y axis should be close to 0. Matching points that do not fit this criterion are discarded. A known rectification process is illustrated in FIG. **3**C.

9. Finally, the remaining matching points are considered true and the disparities for them are calculated. A weighted average of the disparity is taken as the shift between both images. The maximum difference between disparity values is taken as the disparity range.

10. At various stages during GR, if there are not enough feature/matching points remaining, the GR is stopped and returns a failure flag.

In addition, it is possible to find range calibration to the rectification process by finding the shiftI=shift for objects at infinity and defining shiftD=shift-shiftI and disparity D=disparity-shiftI. We then calculate

object distance =
$$\frac{focalLength \cdot baseline}{disparityD \cdot pixelSize}$$
,

where "baseline" is the distance between cameras.

Returning now to the Zoom-in process, in some embodi- 65 ments, for higher ZF than the up-transfer ZF the output is the transformed Tele camera output, digitally zoomed. How-

ever, in other embodiments for higher ZF than the uptransfer ZF there will be no switching from the Wide to the Tele camera output, i.e. the output will be from the Wide camera, digitally zoomed. This "no switching" process is described next.

No Switching

Switching from the Wide camera output to the transformed Tele camera output will be performed unless some special condition (criterion), determined based on inputs 10 obtained from the two camera images, occurs. In other

words, switching will not be performed only if at least one of the following no-switching criteria is fulfilled:

1. if the shift calculated by GR is greater than a first threshold, for example 50 pixels.

- 2. if the disparity range calculated by GR is greater than a second threshold, for example 20 pixels, because in this case there is no global shift correction that will suppress movement/jump for all objects distances (smooth transition is impossible for all objects).
- 20 3. if the effective resolution score of the Tele image is lower than that of the Wide image. In this case, there is no point in performing the transition because no value (i.e. resolution) is gained. Smooth transition is possible but undesirable.
 - 4. if the GR fails, i.e. if the number of matching pairs found is less than a third threshold, for example 20 matching pairs. 5. if, for example, that are imaged onto the overlap area are calculated to be closer than a first threshold distance, for example 30 cm, because this can result in a large image shift to obtain ST.

6. if some objects (for example two objects) that are imaged in the overlap area are calculated to be closer than a second threshold distance, for example 50 cm, while other objects (for example two objects) are calculated to be farther than a third threshold distance for example 10 m. The reason is that the shift between an object position in the Wide and Tele cameras is object distance dependent, where the closer the objects the larger the shift, so an image containing significantly close and far objects cannot be matched by simple transformation (shift scale) to be similar and thus provide ST between cameras.

Zoom-Out:

At high ZF down to slightly below Z_{FT} , the output image is the digitally zoomed transformed Tele camera output. For the down-transfer ZF, the output is a shifted Wide camera output, where the Wide shift correction is performed by the GR algorithm to achieve smooth transition, i.e. with no jump in the ROI region. For lower (than the down-transfer) ZF, the output is basically the down-transfer ZF output digitally zoomed but with gradually smaller Wide shift correction, until for ZF=1 the output is the unchanged Wide camera output.

Note that if a no-switching criterion is not fulfilled, then the camera will output without fusion continuous zoom 55 video mode output images of the object or scene, each output image having a respective output resolution, the video output images being provided with a smooth transition when switching between the lower ZF value and the higher ZF value or vice versa, wherein at the lower ZF value the 60 output resolution is determined by the Wide sensor, and wherein at the higher ZF value the output resolution is determined by the Tele sensor.

FIG. **3**A shows an embodiment of a method disclosed herein for acquiring a zoom image in video/preview mode for 3 different zoom factor (ZF) ranges: (a) ZF range=1: Z_{switch} ; (b) ZF range= Z_{switch} ; Z_{switch} + $\Delta Zoom_{in}$; and (c) Zoom factor range= Z_{switch} + $\Delta Zoom_{in}$: Z_{max}. The description

is with reference to a graph of effective resolution vs. zoom factor (FIG. 4). In step 302, sensor control module 116 chooses (directs) the sensor (Wide, Tele or both) to be operational. Specifically, if the ZF range=1:Z_{switch}, module 116 directs the Wide sensor to be operational and the Tele sensor to be non-operational. If the ZF range is Z_{switch}: $Z_{switch}+\Delta Zoom_{in}$, module 116 directs both sensors to be operational and the zoom image is generated from the Wide sensor. If the ZF range is $Z_{switch} + \Delta Zoom_{in}: Z_{max}$, module **116** directs the Wide sensor to be non-operational and the Tele sensor to be operational. After the sensor choice in step 302, all following actions are performed in video processing core 126. Optionally, in step 304, color balance is calculated if two images are provided by the two sensors. Optionally yet, 15 in step 306, the calculated color balance is applied in one of the images (depending on the zoom factor). Further optionally, in step 308, registration is performed between the Wide and Tele images to output a transformation coefficient. The transformation coefficient can be used to set an AF position 20 in step 310. In step 312, an output of any of steps 302-308 is applied on one of the images (depending on the zoom factor) for image signal processing that may include denoising, demosaicing, sharpening, scaling, etc. In step 314, the processed image is resampled according to the transforma- 25 tion coefficient, the requested ZF (obtained from zoom function 124) and the output video resolution (for example 1080p). To avoid a transition point to be executed at the same ZF, Δ Zoom can change while zooming in and while zooming out. This will result in hysteresis in the sensor 30 switching point.

In more detail, for ZF range 1: Z_{switch} , for ZF < Z_{switch} , the Wide image data is transferred to the ISP in step 312 and resampled in step 314. For ZF range= Z_{switch} : Z_{switch} + $\Delta Zoom_{in}$, both sensors are operational and the zoom image 35 is generated from the Wide sensor. The color balance is calculated for both images according to a given ROI. In addition, for a given ROI, registration is performed between the Wide and Tele images to output a transformation coefficient. The transformation coefficient is used to set an AF 40 position. The transformation coefficient includes the translation between matching points in the two images. This translation can be measured in a number of pixels. Different translations will result in a different number of pixel movements between matching points in the images. This move-45 ment can be translated into depth and the depth can be translated into an AF position. This enables to set the AF position by only analyzing two images (Wide and Tele). The result is fast focusing.

Both color balance ratios and transformation coefficient 50 are used in the ISP step. In parallel, the Wide image is processed to provide a processed image, followed by resampling. For ZF range= $Z_{switch}+\Delta Zoom_{in}$; Z_{max} and for Zoom factor> Z_{switch} , $+\Delta Zoom_{in}$, the color balance calculated previously is now applied on the Tele image. The Tele image 55 data is transferred to the ISP in step **312** and resampled in step **314**. To eliminate crossover artifacts and to enable smooth transition to the Tele image, the processed Tele image is resampled according to the transformation coefficient, the requested ZF (obtained from zoom function **124**) 60 and the output video resolution (for example 1080p).

FIG. **4** shows the effective resolution as a function of the zoom factor for a zoom-in case and for a zoom-out case ΔZoom_{up} is set when one zooms in, and $\Delta \text{Zoom}_{down}$ is set when one zooms out. Setting ΔZoom_{up} to be different from 65 $\Delta \text{Zoom}_{down}$ will result in transition between the sensors to be performed at different zoom factor ("hysteresis") when

zoom-in is used and when zoom-out is used. This hysteresis phenomenon in the video mode results in smooth continuous zoom experience.

In conclusion, dual aperture optical zoom digital cameras and associate methods disclosed herein reduce the amount of processing resources, lower frame rate requirements, reduce power consumption, remove parallax artifacts and provide continuous focus (or provide loss of focus) when changing from Wide to Tele in video mode. They provide a dramatic reduction of the disparity range and avoid false registration in capture mode. They reduce image intensity differences and enable work with a single sensor bandwidth instead of two, as in known cameras.

All patent applications mentioned in this specification are herein incorporated in their entirety by reference into the specification, to the same extent as if each individual patent application was specifically and individually indicated to be incorporated herein by reference. In addition, citation or identification of any reference in this application shall not be construed as an admission that such reference is available as prior art to the present disclosure.

While this disclosure has been described in terms of certain embodiments and generally associated methods, alterations and permutations of the embodiments and methods will be apparent to those skilled in the art. The disclosure is to be understood as not limited by the specific embodiments described herein, but only by the scope of the appended claims.

What is claimed is:

- 1. A dual-aperture zoom digital camera comprising:
- a) a Wide imaging section that includes a fixed focal length Wide lens with a Wide field of view FOV_W and a Wide sensor, the Wide imaging section operative to provide Wide image data of an object or scene;
- b) a Tele imaging section that includes a fixed focal length Tele lens with a Tele field of view FOV_T that is narrower than FOV_W and a Tele sensor, the Tele imaging section operative to provide Tele image data of the object or scene; and
- c) a camera controller operatively coupled to the Wide and Tele imaging sections and configured to evaluate if a no-switching criterion is fulfilled or not fulfilled, wherein at a zoom factor (ZF) value greater than a zoom factor ZF_T =tangent (FOV_{*mide*})/tangent (FO- V_{Tele}), if the no-switching criterion is fulfilled the camera controller is further configured to output a zoom video output image that includes only digitallyzoomed Wide image data, and if the no-switching criterion is not fulfilled, the camera controller is further configured to output a zoom video output image that includes only transformed, digitally zoomed Tele image data.

2. The camera of claim **1**, wherein the ZF value expresses a maximal zoom Zmax.

3. The camera of claim **1**, wherein the no-switching criterion includes a shift between the Wide and Tele images calculated by global registration, the shift being greater than a first threshold.

4. The camera of claim **1**, wherein the no-switching criterion includes a disparity range calculated by global registration, the disparity range being greater than a second threshold.

5. The camera of claim **1**, wherein the no-switching criterion includes an effective resolution of the Tele image being lower than an effective resolution of the Wide image.

6. The camera of claim 1, wherein the no-switching criterion includes a number of corresponding features in the Wide and Tele images being smaller than a third threshold.

7. The camera of claim 1, wherein the no-switching criterion includes a majority of objects imaged in an overlap area of the Wide and Tele images being calculated to be closer to the camera than a first threshold distance.

8. The camera of claim 1, wherein the no-switching criterion includes some objects imaged in an overlap area of the Wide and Tele images being calculated to be closer than a second threshold distance while other objects imaged in the overlap area of the Wide and Tele images being calculated to be farther than a third distance threshold.

9. The camera of claim **1**, wherein the camera controller includes a user control module for receiving user inputs and a sensor control module for configuring each sensor to acquire the Wide and Tele image data based on the user inputs.

10. The camera of claim **9**, wherein the user inputs include a zoom factor, a camera mode and a region of interest.

11. The camera of claim **1**, wherein the Tele lens includes ²⁰ a ratio of total track length (TTL)/effective focal length (EFL) smaller than 1.

12. The camera of claim **1**, wherein the camera controller is further configured to combine in still mode, at a predefined range of ZF values, at least some of the Wide and ²⁵ Tele image data to provide a fused output image of the object or scene from a particular point of view.

13. A method for obtaining zoom images of an object or scene using a dual-aperture zoom digital camera, comprising:

- a) configuring a camera controller to evaluate if a noswitching criterion is fulfilled or not fulfilled;
- b) if the no-switching criterion is fulfilled, configuring the camera controller to output at a zoom factor (ZF) higher than a zoom factor ZF_T =tangent (FOV_{*Wide*})/ tangent (FOV_{*Tele*}) a zoom video output image that ³⁵ includes only digitally-zoomed Wide image data; and
- c) if the no-switching criterion is not fulfilled, configuring the camera controller to output a zoom video output image that includes only transformed, digitally zoomed Tele image data.

14. The method of claim 13, wherein the ZF value expresses a maximal zoom Zmax.

15. The method of claim **13**, wherein the no-switching criterion includes a shift between the Wide and Tele images calculated by global registration, the shift being greater than a first threshold.

16. The method of claim **13**, wherein the no-switching criterion includes a disparity range calculated by global registration, the disparity range being greater than a second threshold.

17. The method of claim **13**, wherein the no-switching criterion includes an effective resolution of the Tele image being lower than an effective resolution of the Wide image.

18. The method of claim **13**, wherein the no-switching criterion includes a number of corresponding features in the Wide and Tele images being smaller than a third threshold.

19. The method of claim **13**, wherein the no-switching criterion includes a majority of objects imaged in an overlap area of the Wide and Tele images being calculated to be closer to the camera than a first threshold distance.

20. The method of claim **13**, wherein the no-switching criterion includes some objects imaged in an overlap area of the Wide and Tele images being calculated to be closer than a second threshold distance while other objects imaged in the overlap area of the Wide and Tele images being calculated to be farther than a third threshold distance.

21. The method of claim **13**, further comprising the step of configuring the camera controller to combine in still mode, at a predefined range of ZF values, at least some of the Wide and Tele image data to provide a fused output image of the object or scene from a particular point of view.

22. The method of claim 13, wherein the step of configuring the camera controller to combine in still mode, at a predefined range of ZF values, at least some of the Wide and Tele image data to provide a fused output image includes configuring the camera controller to combine Wide and Tele image data only in focused areas.

* * * * *